01/04/2019

Current Status:	Baseline
Issue Date:	01/04/2019
Version:	3.1

Table of Contents

1.	Introduction	3		
1.1	Scope	3		
1.2	History of Changes	3		
1.3		4		
1.4	Outstanding Issues	4		
2.	Procedure Description	5		
2.1	Suspension and Direction			
2.2	Notification and Registration			
	2.2.1 Process Flow Diagram	6		
	2.2.2 Process Description	7		
	2.2.3 Lists of Affected Customers			
2.3	Completion	10		
	2.3.1 Process Flow Diagram	10		
2.4	Supplementary Information	13		

1. Introduction

1.1 Scope

This document is the Retail Market Procedure for Supplier of Last Resort

The Procedure applies to all types of metered and unmetered sites and contains the following sub-processes:

- Suspension and Direction
- Notification and Registration
- Completion

1.2 History of Changes

Version	Source of Change	Description of Change
0.1	P Merkens	Initial draft version.
0.2	P Merkens	Updated following NIE review
0.91	P Merkens	Issued for SIG Review
0.92	P Merkens	Update following SIG Workshop
0.93	J-E Smith	Final Draft for Supplier Review prior to SIG Approval
0.94	A Ferguson	Clarification on de-energised sites excluded from SoLR processes.
1.0	A Ferguson	Baseline SIG Approval
2.0	A Ferguson	Baseline CDA Board Approved
		Updated for DR1110/CRID163
2.1	A Ferguson	Updated to reflect MP NI 39 Glossary of Terms
2.1.1	J-E Smith	Updated for DR1144/CRID 182 following instruction from the UR
2.1.2	J-E Smith	Updated following CDA Board Supplier review comments
2.1.3	J-E Smith	Updated for CDA Board review
		Baseline CDA Board Approved/Change Report UR Approved
3.0	NIE Networks	Updated to incorporate change of name from NIE to NIE Networks
3.1	NIE Networks	Updated to incorporate changes to SoLR process to facilitate potential timing issues to complete a SoLR

1.3 Document References

Document	Document Reference
MP NI 14	Readings Processing Non Interval
MP NI 39	NI Market Procedures - Glossary of Terms

1.4 Outstanding Issues

2. Procedure Description


2.1 Suspension and Direction

This section is provided for background and guidance only.

Step	Role	Action	Interface
1	SMO/ Relevant Stakeholder	The SMO or other relevant stakeholder informs the Regulatory Authority of the defaulting Supplier and issues a Suspension Order to the defaulting Supplier.	
	UR	The UR issues written notice to revoke the licence to the defaulting Licensee. This will identify the date and time ("Day 0") at which the licence will be revoked. The UR will simultaneously contact NIE Networks and the Supplier of Last Resort, both verbally and formally in writing, to advise that SoLR is due to commence on Day 0. NIE Networks and the Supplier of Last Resort can prepare for Day 0 but cannot put in motion any action that cannot be reversed.	
2	NIE Networks	Within one day of being informed by UR NIE Networks calculate the percentage market share of the defaulting Supplier and forwards this information to the Supplier of Last Resort.	
3	Regulatory Authority	In the case that the defaulting Supplier is not successful in averting the SoLR event, the Regulatory Authority may suspend the defaulting Supplier and issue the SoLR Direction. The SoLR direction will identify the SoLR event date at which any Registrations will be transferred from the defaulting Supplier.	
4 5	SMO NIE Networks	The SMO terminates the defaulting Supplier and informs NIE Networks of the termination. NIE Networks removes the terminated Supplier from aggregation.	

2.2 Notification and Registration

2.2.1 Process Flow Diagram



2.2.2 Process Description

Step	Role	Action	Interface
1, 2, 3	NIE Networks	NIE Networks receives the SoLR Direction from the Regulatory Authority.	
	Networks	NIE Networks will cancel Changes of Supplier that are in progress to the terminated Supplier.	
		NIE Networks will process any Changes of Supplier that are in progress from the terminated Supplier to be effective at the SoLR event date.	
		NIE Networks will provide Secure Meters with the SoLR ID, existing Keypad Premise Number for defaulting Supplier sites and the required TCC of the SoLR.	CSV to Secure Meters
		NIE Networks will receive new Keypad Premise Numbers for the SoLR from Secure Meters.	CSV to NIE Networks
		NIE Networks will issue via a secure server a list(s) of affected customers to the Supplier of Last Resort.	CSV to Supplier of Last Resort
		NIE Networks will instruct Secure Meters to perform to the SoLR process.	Email
4	Supplier of Last Resort	Supplier of Last Resort will receive the detailed list(s) of affected Customers (a separate list will be issued for Credit, Keypad as applicable).	CSV from NIE Networks
		Upon request by the Supplier of Last Resort NIE Networks can provide a separate sample CSV containing the structure of the file.	
5	Supplier of Last Resort	For energised sites, the Supplier of Last Resort will inform the affected Customers by letter of their options.	Letter to Customers
		For keypad metered Customers the letter must include the new Keypad Premises Number.	
6	Customer	Customer receives letter from Supplier of Last Resort.	Letter from SoLR

Step	Role	Action	Interface
7	NIE Networks	NIE Networks processes the SoLR Change of Suppliers. NIE Networks will estimate readings for metered Non-Interval Meter Points, dated as at the SoLR event date. See MP NI 14 Readings Processing Non Interval for estimation rules. Note that in the absence of actual reads, estimates will be used to complete a SoLR transfer to a Supplier of Last Resort. Supplier Provided Readings dated after the SoLR event date will not be used for the Change of Supplier.	
8, 7	NIE Networks	For Meter Points after the event date on the SoLR Direction, NIE Networks will issue via a secure server a Residual List(s) of affected Customers to the Supplier of Last Resort.	CSV to Supplier of Last Resort
9	Supplier of Last Resort	Receive Residual List(s) of affected Customers.	CSV from NIE Networks

2.2.3 Lists of Affected Customers

The list(s) of affected Customers provided to the Supplier of Last Resort contains the following information for each MPRN affected for Credit and Keypad (excluding De-energised and Unmetered sites), as applicable.

MPRN
Connection System
Voltage
Tariff Group
Register Group
DUoS Tariff
Meter Category
PPM Meter Flag
KPN Number

Meter Type

MIC

Meter Configuration Code

Load Profile

Load Factor

Months

Read Cycle

SIC Code

Address Type A1

Address Type A2

Address Type A3

Customer Name

Customer Contact Details

MESN

CSSN

TCC

CSC

Number of Meters


Serial Number

Number of Registers

Meter Register Sequence

2.3 Completion

2.3.1 Process Flow Diagram



2.3.2 Process Description

Step	Role	Action	Interface
1	NIE Networks	When a Registration has been processed for a Supplier of Last Resort, NIE Networks will register the Meter Point to the Supplier of Last Resort as at the date of the SoLR Event. NIE Networks will register the Meter Point to the Supplier of Last Resort as at the date of the SoLR Event for de-energised and for un-metered sites.	
2	NIE Networks	For keypad metered sites, NIE Networks will order new keypad premises cards after completion of the transfer on the Keypad Transaction System and send these directly to the Customer. No retained credit process is performed.	Keypad Premise Card to Customer
3, 4	NIE Networks	On completion the terminated Supplier will be advised: • for Non-Interval metered Meter Points, of closing readings with any estimated or actual consumption since the last billed reading; and • for unmetered Meter Points, of unmetered consumption since the last bill date.	310 to Term. Supplier 701 to Term. Supplier
5, 6	NIE Networks	For each Meter Point registered to a Supplier of Last Resort, at the point the Registration is processed and is valid, the Supplier of Last Resort will be advised of: • The effective date of the Registration to the Supplier of Last Resort, together with confirmation of the connection and Customer details held by NIE Networks and; • for Interval metered Meter Points, details of Interval metering; or • for Non-Interval metered Meter Points, details of metering together with the Load Profile, EUF and the actual (where available) or estimated opening readings; or	Flat Files
		For Unmetered Meter Points, the Supplier of Last Resort will be advised of the unmetered characteristics.	700 to Supplier of Last Resort

Step	Role	Action	Interface
		For each de-energised Meter Point registered to a Supplier of Last Resort, the Supplier of Last Resort will be advised of: • The effective date of the Registration to the Supplier of Last Resort, together with confirmation of	Flat File
		the connection held by NIE Networks and; for Interval metered Meter Points, details of Interval metering; or for Non-Interval metered Meter Points, details of metering together with the Load Profile, EUF and the actual (where available) or estimated opening readings; or for unmetered Meter Points, details of the Unmetered Inventory	700
7	NIE Networks	Where the Meter Point forms part of a trading site, NIE Networks will inform the SMO of the Change of Supplier.	

2.4 Supplementary Information

For keypad metered Meter Points:

• The retained credit process is not performed as part of the keypad meter transfer.

NIE Networks will consider any open Fieldwork service orders on a case by case basis and cancel these if appropriate.

Registrations are locked in to the Supplier of Last Resort for a standard period of twenty days.

The terminated Supplier does not receive the Change of Supplier Confirmation (105L) and Notification to Old Supplier (110) market messages when Meter Points are registered under a Supplier of Last Resort process.